



TRM702AU

FM RF 2 binary inputs battery powered

Functions

- ETS additional functions: +6 scenes, operating mode on/off, 1 up/down button control, push-button, 2 x alarm, status display
- reset function (to factory setting)
- scene saving lockable
- scene opening via KNX radio appliances
- quicklink functions: switching, 2 scenes, time switching, NO contact push-button, forced control

Configuration

- confectioned, with 2-core cable

Controls and indicators

Indicator lamp	yes
With LED control	yes

- with manual operation on/off
- with configuration and function button
- Activation, for example through switch, push-buttons, timer

Connectivity

Bus system LON	no
Radio protocol	KNX Radio
Receiver category	2

- with independent, mains supplied, binary input for potential-free contact

Voltage

Generated supply voltage	no
Input voltage	3 V

Electric current

Input signal current	33 μ A
Number of entry circuits	2

Frequency

Radio reception frequency	868,3 MHz
Radio transmission/reception frequency	868,3 MHz

Power

Electronic transformers	600 W
Radio transmission power	< 10 mW
- low intrinsic energy requirement	

Measurement

Input scanning voltage	5 V
Relative humidity (without condensation)	0 65 % (without condensation)

Detection

Dimensions, sensor (Ø x H)	53 x 30 mm
----------------------------	------------

Materials

Colour independent of design lines	light grey
------------------------------------	------------

Dimensions

Ø	53 mm
Height	30 mm

Fluorescent bulbs control

Fluorescent lamps parallel compensated	36 W
----------------------------------------	------

LED control

- with transmission status and control LED for On/Off
- with configuration and function LEDs

Incandescent bulbs control

230 V incandescent lamps and halogen lamps	1500 W
--------------------------------------------	--------

Installation, mounting

- for installation behind flush-mounted inserts

Connection

- with screw-in lift terminals
- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

Cable

Binary cable length, extendable to	max. 5 m
Binary cable length	~ 20 cm

Settings

Supported configuration modes	system , easy , PB
-------------------------------	--------------------

- toolless quicklink configuration using buttons and LED display

Equipment

Number of radio channels	1
Number of quicklink links	max. 20 transmitter/receiver
Transmitter duty cycle	1 %

Use conditions

Operating temperature	-5 45 °C
-----------------------	----------

Identification

Application, usage	KNX radio - actuators
Product family	product family: output
Main design line	Electronics platform
Secondary design line(s)	Berker.Net
