

### Motor Protection Circuit Breaker 1.6... 2.5 Amp



- Manual motor starting permits on / off motor control for non-severe duty
- Available in a wide range of motor sizes to suit your installation type
- Wide range of accessories for application flexibility

Representative Photo Only  
(actual product may vary based on configuration selections)

#### SPECIFICATIONS

Product Series	Motor Protection
Component Type Motor Control and Drives	Motor Protection Circuit Breaker
Approx. kW (AC 3, 400/415 V AC)	0.75 kW
kW Rating, AC-3, 415V	0.75 kW @415V
kW Rating, AC-3, 415V, Max	0.75 kW @415V max
I <sub>e</sub> , Rated Operational Current, nom	2.5 A <sub>nom</sub>
I <sub>r</sub> , Thermal Trip Setting, Min	1.6 A min
I <sub>r</sub> , Thermal Trip Setting, Max	2.5 A max
I <sub>m</sub> , Magnetic Trip Current	35 A
I <sub>cu</sub> , Rated Ultimate Short-Circuit Breaking Capacity, 400V AC	100 kA @400VAC
I <sub>cu</sub> , Rated Ultimate Short-Circuit Breaking Capacity, 415V AC	100 kA @415VAC
IP Rating	IP2X

#### REFERENCES

IECEX Certificate	-
Supplier Declaration of Conformity:	-
Installation Guide:	-
User Manual:	-
Manufacturer Datasheet:	-
Manufacturer Catalogue & Product Selection:	-