

Constant-current LED Driver dimmable via phase-cut and 1–10V



Description	Output current	Output power	Output voltage range	Input voltage	Size	Order No.
LCBI 10W 180mA phase-cut/1–10 V SR	180mA	10W	21–46V	220~240V	102 x 51 x 30mm	87500273
LCBI 10W 350mA phase-cut/1–10 V SR	350mA	10W	13.5–30V	220~240V	102 x 51 x 30mm	87500274
LCBI 10W 500mA phase-cut/1–10 V SR	500mA	15W	10–21.5V	220~240V	102 x 51 x 30mm	87500275
LCBI 20W 350mA phase-cut/1–10 V SR*	350mA	20W	27–54V	220~240V	102 x 51 x 30mm	87500276
LCBI 20W 500mA phase-cut/1–10 V SR*	500mA	20W	19–38V	220~240V	102 x 51 x 30mm	87500277

*no ENEC certification

▼ At a glance: TALEXdriver ADVANCED phase-cut/1–10V

- ___ Constant current LED Driver
- ___ Dimmable via phase-cut
- ___ Dimmable via 1...10V
- ___ Typ. Dimming range 10–100 % (depending on dimmer)
- ___ Nominal life-time up to 50,000 h
- ___ SELV
- ___ 5 years guarantee